

# seisfile-seedlinkclient(1)

## Name

seisfile-seedlinkclient - Example client to stream miniseed over seedlink.

## Synopsis

**seisfile seedlinkclient** [-vV] [--help] [-b=<start>] [-e=<end>] [-h=<host>] [--iout=<ioutFile>] [--itype=<infoType>] [--max=<maxRecords>] [-o=<outputFile>] [-p=<port>] [--timeout=<timeoutSec>] [-c=<channel>[, <channel>...]]... [-l=<location>[,<location>...]]... [-n=<network>[,<network>...]]... [-s=<station>[, <station>...]]...

## Description

Example client to stream miniseed over seedlink.

## Options

**-b, --start, --starttime=<start>**

Limit results to time series samples on or after the specified start time

**-c, --channel=<channel>[,<channel>...]**

list of channels to search

**-e, --end, --endtime=<end>**

Limit results to time series samples on or before the specified end time

**-h, --host=<host>**

host to connect to, defaults to IRIS, rtserve.iris.washington.edu

**--help**

display a help message

**--iout=<ioutFile>**

info out file

**--itype=<infoType>**

info typ, ex STREAMS

**-l, --location=<location>[,<location>...]**

list of locations to search

**--max=<maxRecords>**

number of packets to receive before ending the connection, defaults to 10

**-n, --network=<network>[,<network>...]**

list of networks to search

**-o, --output=<outputFile>**

Output file (default: print to console)

**-p, --port=<port>**

port to connect to, defaults to IRIS, 18000

**-s, --station=<station>[,<station>...]**

list of stations to search

**--timeout=<timeoutSec>**

timeout seconds, defaults to 120

**-v, --verbose**

Verbose

**-V, --version**

Print version and exit

## Examples

Ask for a few packets of HHZ data from station CO.HODGE, and output to a file.

```
> seedlinkclient -n CO -s HODGE -c HHZ -o hodge.mseed --max 3 -v
send 'HELLO'
SeedLink v3.1 (2018.078 RingServer) :: SLPROTO:3.1 CAP EXTREPLY NSWILDCARD BATCH WS:13
IRIS DMC RTSERVE3 ADC1 Ring Server
line 1 :SeedLink v3.1 (2018.078 RingServer) :: SLPROTO:3.1 CAP EXTREPLY NSWILDCARD
BATCH WS:13
line 2 :IRIS DMC RTSERVE3 ADC1 Ring Server
send 'STATION HODGE CO'
OK
send 'SELECT HHZ.D'
OK
send 'SELECT ??HHZ.D'
OK
send 'DATA'
OK
send 'END'
hasNext(): blocking read for 3 bytes, available=0
readPacket(): blocking read for 520 bytes, available=4680
Got a packet: D00BCC CO HODGE 00 HHZ 2023,038,17:31:47.6700
D CO.HODGE.00.HHZ 2023,038,17:31:47.6700 4.13 413
hasNext(): blocking read for 3 bytes, available=4160
readPacket(): blocking read for 520 bytes, available=4160
Got a packet: D00BCD CO HODGE 00 HHZ 2023,038,17:31:51.8000
D CO.HODGE.00.HHZ 2023,038,17:31:51.8000 3.86 386
hasNext(): blocking read for 3 bytes, available=3640
readPacket(): blocking read for 520 bytes, available=3640
Got a packet: D00BCE CO HODGE 00 HHZ 2023,038,17:31:55.6600
D CO.HODGE.00.HHZ 2023,038,17:31:55.6600 3.67 367
send 'BYE'
Finished: 2023-02-07T17:32:42.555035Z
```